

ARL24/D FLEXICONTROL

Wireless Transmission Accessories
Compatible With All Radiocontact
Video / Audio Transmission Systems

RCL

RADIOCONTACT LTD est 1973

2-CHANNEL RELAY CONTROL ENCODER/DECODER

The ARL24/D utilises the audio channel of a wireless transmission system to transmit two independent input signals e.g. from a PIR, fire detector, call button etc. connected to a video transmitter over air to a video receiver in order to control external devices such as sounders, cameras, VCR etc.

Main Features

- 12V DC Operation
- Low Current Consumption <120mA (On State)
- Input: 2 independent volt free N.O. relay Contacts
- Output: 2 independent Change Over Relay Contacts
- Relay Contacts rated at 1A @ 24 V DC
- Lightweight Design
- Supplied With Pole Mounting Kit and User manual
- IP65 Sealed Housing
- Uses Short Pulsed DTMF Tones For Accurate And Robust Control
- Temperature 0°C to +50°C

Applications

- Remote PIR trigger Indication
- Remote Call Button
- Remote recording Trigger
- Remote Gate Operation
- Remote Barrier Operation
- Remote Fire Detection

